

***This clamp meter is suitable for measuring low-voltage circuits.***

# **DIGITAL CLAMP METER**

**Part No. TA451D-2**

**List Price: JPY 10,000**

Resolution  
**0.01A**

Conductor  
**φ30 mm**

AC **A**

DC **V**  
AC **V**



## **FEATURES**

- ◆ Clamp opening size : 25mm
- ◆ Frequency measurement by clamping and using test leads
- ◆ Data hold
- ◆ Continuity check buzzer
- ◆ Auto power off(30min)
- ◆ Low battery power indication
- ◆ Battery: AAA battery ×2

## **SPECIFICATIONS**

	Measuring range	Best accuracy	Resolution
AC/A	40/400A	±(1.9%+5)	0.01A
AC/V	400/600V	±(1.5%+5)	0.1V
DC/V	400/600V	±(1%+2)	0.1V
Resistance	400Ω	±(1%+2)	0.1Ω
Frequency(A)	20 ~ 4k/10kHz	±(0.1%+1)	0.01Hz
Frequency(V)	4k/40k/400k/1MHz	±(0.1%+1)	0.01kHz
Continuity	Buzzer sounds at less than approx. 40Ω, Open voltage : approx. 1.5V		