AC / DC 2-StageVacuum Pump

TASCO
High Quality Products

New Dual-Power 2-Stage Vacuum Pump — AC 100–240V & Lithium-Ion Battery Compatible



Free Air Displacement	57 ℓ/min
Ultimate Vacuum	2.5 Pa

NET WEIGHT
3.3 kg

ICHINEN TASCO CO.,LTD.

Ultra-Lightweight 3.3 kg Body with Ergonomic Handle



Dual Power Supply: AC 100V-240V ⇔ Lithium-Ion Battery





Easy Power Access Anywhere



AC 100–240V Power
Enables Extended Operation



Compact & Lightweight 2-Stage Design



Built-in Solenoid Valve as Standard

AC/DC Adapter or Battery

2 Stage

Solenoid Valve

Light Weight 3.3kg Net Weight

For Makita battery DC18V only.

Specification

AC / DC 2-STAGE VACUUM PUMP

Part No.	TA150ZMD-1-EXP	TA150ZMD-1H
Set Contents	Main Unit + AC Adapter	Main Unit Only
Free Air Displacement	2.0CFM (57L/min.)	
Rotor	Two Stage	
Ultimate Vacuum	19 microns	
Voltage	Makita Battery DC18V (Sold separately) AC Adapter100～240V	
Motor / RPM	90W / 2880-4000 r.p.m.	
Vacuum Pump Oil Capacity	140 ml	
Intake Fitting	5/16" (1/2-20UNF)	
Dimensions / Weight	107W × 210D × 215H mm / 3.1kg	
Accessories	◆Pump Oil ◆1/4″ Male × 5/16″ Female adapter (TA159P-4) ◆AC ADAPTER	◆Pump Oil ◆1/4″ Male × 5/16″ Female adapter (TA159P-4)

※Battery and charger not included.
Only use a Makita 18V lithium-ion battery.



Featuring an ultra-compact design, the main unit and a Complete set of evacuation tools fit neatly I n the dedicated case.

ICHINEN TASCO CO.,LTD.

Instagram
TASCO_OVERSEAS